

### Storage Card

The power management of the GNS3000 is prepared to switch off the device automatically after 15min.

This time default is fixed and cannot be changed by the user.

The Power Management of the GNS3000 was set up for 2 use cases.

1. Automatic shutdown of the device when not in use.
2. Operation of the device in fixed installation when the on/off switch is not accessible.

To avoid the unwanted shutdown of the GNS3000, the function only comes into effect under certain conditions. The following operation conditions are considered:

1. GNS3000 is supplied with power via an external power supply.
2. The USB connection is active.
3. The GNS3000 is switched on and GPS logging is switched on.

The countdown of the automatic shutdown starts only if **none** of the above 3 conditions is met.

As soon as at least one of the above conditions occurs, the countdown is stopped and reset.

The GNS3000 therefore does **not** switch off automatically when

1. It is powered via an external power supply **or**
2. USB connection is active **or**
3. Logging on storage card is activated.

The GNS3000 switches on again as soon as the external power supply is switched on again.

Of course, the device can also be switched on again by switching the on/off switch to 'Off' followed by 'On'.